

7GN1291U47 ROTARY CAM SWITCH 7GN SERIES, ON-OFF SWITCH 2 POLES 16A, FOR SNAP ON FRONT MOUNTING WITH BLACK HANDLE FOR HOLE Ø22MM FIXING, FRONT PLATE 48X48MM



Product designation				Rotary cam
-				switches
Product type designatic General characteristics				7GN12
				91 - ON/OFF
Switching diagram				switch 2 poles
N° of elements				1
				U47 - Snap on
Maximutia au farmas				fron mounting
Mounting form				with black handle for hole diam.
				22mm finxing
Contact characteristics				J. J
Rated insulation voltage	e Ui			
		IEC/EN	V	690
		UL/CSA	V	600
Rated impulse withstan			kV	6
Conventional free air th	ermal current Ith		^	4.0
		IEC/EN UL/CSA	A A	16 15
Rated operational volta		00/007	 V	480
Rated operational impu	-		kV	4
	short-circuit protection In (gG)			
		10kA	А	16
		15kA	А	10
		25kA	А	10
Rated short time curren	it Icw			
<u> </u>		1s	kA	200
Conductivity Operational current le I				10/5 mA/V
Operational current le r	AC1/AC21A			
			А	16
	AC15			
		110V	А	10
		220/230V	А	8
		380/400V	А	4
		660/690V	A	1.5
Rated operational powe				
	Three-phase AC-3	220/2201/	L\\/	2.5
		220/230V 380/440V	kW kW	2.5 4
		500/690V	kW	5.5
	Single-phase AC-3			
		110V	kW	0.8
		220/230V	kW	1.5
		380/440V	kW	2.2

7GN1291U47

The characteristics described in this document are subject to updates or modifications at any time. The descriptions, technical and functional information, illustrations and instructions in this brochure are purely illustrative, and are consequently not contractually binding



7GN1291U47 ROTARY CAM SWITCH 7GN SERIES, ON-OFF SWITCH 2 POLES 16A, FOR SNAP ON FRONT

MOUNTING WITH BLACK HANDLE FOR HOLE Ø22MM FIXING, FRONT PLATE 48X48MM

	Three-phase AC23A			
		220/230V	kW	3
		380/440V	kW	5.5
		500/690V	kW	7.5
	Single-phase AC23A			
		110V	kW	0.8
		220/230V	kW	1.7
		380/440V	kW	
Deted an exetion of a		300/440 V	KVV	3
Rated operational c				
	DC21A			
		48V	А	12
		60V	А	12
		110V	А	4
		220V	А	0.6
		440V	А	0.25
	DC23A (poles in series)			0.20
		24V	А	10 (1)
		24 v 48 V	A	
				10 (2)
		60V	A	10 (3)
		110V	А	5 (3)
		220V	A	5 (4)
	DC13			
		24V	А	12
		48V	А	10
		60V	А	8
		110V	A	1
		220V	A	0.4
		440V	A	0.15
Devues dis sis sties		440 V	 	
Power dissipation			VV	0.8
Mechanical features				1.40
Terminals screw				M3
Tightening torque for	or terminals max		Nm	0.5
Conductor size				
	AWG - Rigid cable			
		min	AWG	20
		Max	AWG	12
	AWG - Flexible cable		Ŧ	
		min	AWG	20
		Max	AWG	14
	Conductor size (IEC) - Flexible cable	<u>.</u>	~	0.5
		min	mm²	0.5
		Max	mm²	2.5
	Conductor size (IEC) - Rigid cable			
		min	mm²	0.5
		Max	mm²	2.5
Mechanical life			cycles	3x10 ⁶
JL technical data			.,	
Notor power for dire	ect-on-line control			
	for three-phase motor			
	וטו נווופפ-טומצב וווטנטו	40017		1 E
		120V	HP	1.5
		240V	HP	3
	for single-phase motor			
		120V	HP	0.5
		240V	HP	1

⁷GN1291U47




7GN1291U47 ROTARY CAM SWITCH 7GN SERIES, ON-OFF SWITCH 2 POLES 16A, FOR SNAP ON FRONT MOUNTING WITH BLACK HANDLE FOR HOLE Ø22MM FIXING, FRONT PLATE 48X48MM

ENERGY AND AUTOMATION

Ambient conditions


Temperature

Operating temperature				
	min	°C	-25	
	max	°C	+55	
Storage temperature				
	min	°C	-40	
	max	°C	+70	
Resistance & Protection				
Frontal IP degree			IP40	
Terminals IP degree			IP00	
Dimensions				



Series	Dimensions		L			
	□A	E	1	2	3	8
7GN12	48	26.5	58	67.7	77.4	125.9
7GN20	48	26.5	58	67.7	77.4	125.9
7GN25	48	26.5	62.4	76	89.6	157.6

Wiring diagrams



Certifications and compliance

Complianc	e
	CSA C22.2 n° 14
	IEC/EN/BS 60947-1
	IEC/EN/BS 60947-3
	IEC/EN/BS 60947-5-1
	UL60947-4-1
Certificate	3
	cCSAus
	EAC
	UL
ETIM class	ification
7GN1291U47	The characteristics described in this document are subject to updates or modifications at any time. The descriptions, technical and functional information, illustrations and instructions in this brochure are purely illustrative, and are consequently not contractually binding 3/4



ENERGY AND AUTOMATION

7GN1291U47 ROTARY CAM SWITCH 7GN SERIES, ON-OFF SWITCH 2 POLES 16A, FOR SNAP ON FRONT MOUNTING WITH BLACK HANDLE FOR HOLE Ø22MM FIXING, FRONT PLATE 48X48MM

ETIM 8.0

EC001029 -Selector switch, complete