



## ROTARY CAM SWITCH 7GN SERIES, MULTI-STEP 0-1-2-3, 2 POLES 32A, FOR FRONT MOUNTING WITH BLACK HANDLE, FRONT PLATE 65X65MM

Product designation Product type designation	on			Rotary cam switches 7GN32		
General characteristics						
Switching diagram				124 - Multi-step 0-1-2-3 2 poles		
N° of elements				3		
Mounting form				U - Front mounting with black handle		
Contact characteristics						
Rated insulation voltage	e Ui					
		IEC/EN UL/CSA	V V	690 600		
Rated impulse withstan	d voltage Uimp		kV	6		
Conventional free air th	ermal current Ith					
		IEC/EN	Α	32		
		UL/CSA	Α	40		
Rated operational volta			V	480		
Rated operational impu			kV	4		
Maximum fuse size for	short-circuit protection In (gG)					
		10kA	Α	32		
		15kA	A	32		
		25kA	A	32		
Rated short time currer	at low	50kA	Α	32		
	it icw	1s	kA	800		
Conductivity				10/5 mA/V		
Operational current le I						
	AC1/AC21A		•	00		
	1015		Α	32		
	AC15	440\/	۸	25		
		110V	A	25		
		220/230V 380/400V	A A	20 10		
		660/690V	A	2		
Rated operational power	er in AC	000/030 V				
rated operational power	Three-phase AC-3					
	Times phase file s	220/230V	kW	7.5		
		380/440V	kW	11		
		500/690V	kW	11		
	Single-phase AC-3					
		110V	kW	2.2		
		220/230V	kW	4		
		380/440V	kW	6.5		
	Three-phase AC23A					
		220/230V	kW	8		
		380/440V	kW	15		
	Oire alse alse as A OOOA	500/690V	kW	18.5		
	Single-phase AC23A	4401	1444	2.2		
		110V	kW kW	2.2		
		220/230V 380/440V	kW	4 7.5		
		300/440 V	r\ v V	7.5		





## ROTARY CAM SWITCH 7GN SERIES, MULTI-STEP 0-1-2-3, 2 POLES 32A, FOR FRONT MOUNTING WITH BLACK HANDLE, FRONT PLATE 65X65MM


Rated operational cui				
	DC21A	40)/		00
		48V	A	32
		60V	A	32
		110V	A	6
	DC00A (redection region)	220V	Α	0.9
	DC23A (poles in series)	0.41/		00 (4)
		24V	A	32 (1)
		48V	A	32 (2)
		60V	A	32 (3)
		110V	A	15 (3)
	D040	220V	Α	12 (4)
	DC13	0.41/	^	20
		24V	A	32
		48V	A	25
		60V	A	16
		110V	A	3
D		220V	Α	0.5
Power dissipation			W	1.5
Mechanical features				N44
Terminals screw				M4
Tightening torque for	terminals max		Nm	1.2
Conductor size				
	AWG - Rigid cable			
		min	AWG	16
		Max	AWG	8
	AWG - Flexible cable			
		min	AWG	16
		Max	AWG	10
	Conductor size (IEC) - Flexible cable			
		min	mm²	1.5
		Max	mm²	4
	Conductor size (IEC) - Rigid cable			
		min	mm²	1.5
		Max	mm²	6
Mechanical life			cycles	5x10 <sup>6</sup>
UL technical data				
Motor power for direc	ct-on-line control			
	for three-phase motor			
		120V	HP	5
		240V	HP	10
		480V	HP	15
		600V	HP	15
	for single-phase motor			
		120V	HP	2
		240V	HP	5
Ambient conditions				
Temperature				
	Operating temperature			
	· · · ·	min	°C	-25
		max	°C	+55
	Storage temperature			
		min	°C	-40
		max	°C	+70


**ENERGY AND AUTOMATION** 

ROTARY CAM SWITCH 7GN SERIES, MULTI-STEP 0-1-2-3, 2 POLES 32A, FOR FRONT MOUNTING WITH BLACK HANDLE, FRONT PLATE 65X65MM

# Resistance & Protection Frontal IP degree Terminals IP degree IP00

#### **Dimensions**






Standard drillings for 7GN125.

Drillings on request for 4 screws fixing (4V version).

Series	Dimensions								L Number of elements												
	□A	С	ØD	ØD1	ØD2	Е	ØG	□K	□N	1	2	3	4	5	6	7	8	9	10	11	12
7GN12	48	39.5	39	12	5	26.5	38	36	6	36.1	45.8	55.5	65.2	74.9	84.6	94.3	104	113.7	123.4	133.1	142.8
7GN20	48	39.5	39	12	5	26.5	38	36	6	36.1	45.8	55.5	65.2	74.9	84.6	94.3	104	113.7	123.4	133.1	142.8
7GN25	48	39.5	43	12	5	26.5	38	36	6	40.5	54.1	67.7	81.3	94.9	108.5	122.1	135.7	147.3	162.9	176.5	190.1
7GN32	65	53	58	14	5	34.5	58.5	48	7	46.5	61.6	76.7	91.8	106.9	122	137.1	152.2	167.3	182.4	197.5	212.6
7GN40	65	53	58	14	5	34.5	58.5	48	7	46.5	61.6	76.7	91.8	106.9	122	137.1	152.2	167.3	182.4	197.5	212.6
7GN63	65	53	62	14	5	34.5	58.5	48	7	50.3	68.4	86.5	104.6	122.7	140.8	158.9	177	195.1	213.2	231.3	249.4
7GN125	90	70.5	86	16	6	41.5	84	68	9	67.3	96.4	125.5	154.6	183.7	220.3	249.4	278.5	307.6	336.7	365.8	394.9

### Wiring diagrams



#### Certifications and compliance

Compliance

CSA C22.2 n° 14

IEC/EN/BS 60947-1

IEC/EN/BS 60947-3 IEC/EN/BS 60947-5-1

UL60947-4-1

Certificates

cCSAus

EAC

UL

ETIM classification

**ETIM 8.0** 

EC001029 -Selector switch, complete