

# **GX40136U** ROTARY CAM SWITCH GX SERIES, MULTI-STEP 0-1-2-3, 3 POLES 40A, FOR FRONT MOUNTING WITH BLACK HANDLE, FRONT PLATE 65X65MM

| Product designation  |          |                  | Rotary cam                                 |  |
|--|----------|------------------|--|--|
| Product type designation                                       |          | switches<br>GX40 |  |  |
| General characteristics  |          |                  | C// IC                                     |  |
| Switching diagram  |          |                  | 136 - Multi-step<br>0-1-2-3 3 poles        |  |
| N° of elements   |          |                  | 5  |  |
| Mounting form  |          |                  | U - Front<br>mounting with<br>black handle |  |
| Contact characteristics  |          |                  |  |  |
| Rated insulation voltage Ui                                    |          |                  |  |  |
|  | IEC/EN   | V                | 690  |  |
|  | UL/CSA   | V                | 600  |  |
| Rated impulse withstand voltage Uimp                           |          | kV               | 6  |  |
| Conventional free air thermal current Ith                      |          |                  |  |  |
|  | IEC/EN   | A                | 40   |  |
| Detect encretional valters                                     | UL/CSA   | A<br>V           | 40   |  |
| Rated operational voltage<br>Rated operational impulse voltage |          | kV               | 440  |  |
| Maximum fuse size for short-circuit protection In (gG)         |          | ĸv               | 4  |  |
| Maximum ruse size for short-circuit protection in (gG)         | 10kA     | А                | 40   |  |
|  | 15kA     | A                | 35   |  |
|  | 25kA     | A                | 35   |  |
| Rated short time current Icw                                   |          |                  |  |  |
|  | 1s       | kA               | 1000                                       |  |
| Conductivity   |          |                  | 10/5 mA/V                                  |  |
| Operational current le IEC/EN                                  |          |                  |  |  |
| AC1/AC21A  |          |                  |  |  |
|  |          | Α                | 40   |  |
| AC15   |          |                  |  |  |
|  | 110V     | A                | 25   |  |
|  | 220/230V | A                | 22   |  |
|  | 380/400V | A                | 12   |  |
|  | 660/690V | A                | 2  |  |
| Rated operational power in AC<br>Three-phase AC-3              |          |                  |  |  |
| Thee-phase AC-5  | 220/230V | kW               | 7.5  |  |
|  | 380/440V | kW               | 15   |  |
|  | 500/690V | kW               | 15   |  |
| Single-phase AC-3  |          |                  |  |  |
|  | 110V     | kW               | 2.2  |  |
|  | 220/230V | kW               | 4.4  |  |
|  | 380/440V | kW               | 7  |  |
| Three-phase AC23A  |          |                  |  |  |
|  | 220/230V | kW               | 9  |  |
|  | 380/440V | kW               | 18.5                                       |  |
|  | 500/690V | kW               | 15   |  |
| Single-phase AC23A   |          |                  |  |  |
|  | 110V     | kW               | 3  |  |
|  | 220/230V | kW               | 5.2  |  |
| Pated operational current in DC                                | 380/440V | kW               | 7.5  |  |

#### Rated operational current in DC

GX40136U

OVE: electric ENERGY AND AUTOMATION

GX40136U ROTARY CAM SWITCH GX SERIES, MULTI-STEP 0-1-2-3, 3 POLES 40A, FOR FRONT MOUNTING WITH BLACK HANDLE, FRONT PLATE 65X65MM

|                                   | DC21A  |  |                                       |  |
|-----------------------------------|--|--|---------------------------------------|--|
|                                   | 50211  | 48V  | А                                     | 40                                     |
|                                   |  | 60V  | А                                     | 40                                     |
|                                   |  | 110V   | А                                     | 6                                      |
|                                   |  | 220V   | A                                     | 0.8                                    |
|                                   |  | 440V   | A                                     | 0.25                                   |
|                                   | DC23A (poles in series)                      | -  |                                       |  |
|                                   |  | 24V  | А                                     | 40 (1)                                 |
|                                   |  | 48V  | А                                     | 40 (1)                                 |
|                                   |  | 60V  | А                                     | 40 (3)                                 |
|                                   |  | 110V   | А                                     | 40 (3)                                 |
|                                   |  | 220V   | А                                     | 12 (4)                                 |
|                                   | DC13   |  |                                       |  |
|                                   |  | 24V  | А                                     | 40                                     |
|                                   |  | 48V  | А                                     | 32                                     |
|                                   |  | 60V  | А                                     | 16                                     |
|                                   |  | 110V   | А                                     | 3                                      |
|                                   |  | 220V   | А                                     | 0.5                                    |
|                                   |  | 440V   | A                                     | 0.15                                   |
| Power dissipation                 |  |  | W                                     | 1.6                                    |
| Mechanical features               |  |  |                                       |  |
| Terminals screw                   |  |  |                                       | M4                                     |
| Tightening torque for te          | rminals max                                  |  | Nm                                    | 1.2                                    |
| Conductor size                    |  |  |                                       |  |
|                                   | AWG - Rigid cable                            |  |                                       |  |
|                                   | - <b>3</b> · · · · · ·                       | min  | AWG                                   | 16                                     |
|                                   |  | Max  | AWG                                   | 8                                      |
|                                   | AWG - Flexible cable                         |  |                                       |  |
|                                   |  | min  | AWG                                   | 16                                     |
|                                   |  | Max  | AWG                                   | 10                                     |
|                                   | Conductor size (IEC) - Flexible cable        |  |                                       |  |
|                                   |  | min  | mm²                                   | 1.5                                    |
|                                   |  | Max  | mm²                                   | 6                                      |
|                                   | Conductor size (IEC) - Rigid cable           |  |                                       |  |
|                                   | ( , 3  | min  | mm²                                   | 1.5                                    |
|                                   |  | Max  | mm²                                   | 10                                     |
| Mechanical life                   |  |  | cycles                                | 1X10 <sup>6</sup>                      |
| UL technical data                 |  |  | ļ                                     |  |
| Motor power for direct-           | on-line control                              |  |                                       |  |
|                                   |  |  |                                       |  |
|                                   | for three-phase motor                        |  |                                       |  |
|                                   | for three-phase motor                        | 120V   | HP                                    | 5                                      |
|                                   | for three-phase motor                        | 120V<br>240V                                       | HP<br>HP                              | 5<br>10                                |
|                                   | for three-phase motor                        |  |                                       |  |
|                                   | for three-phase motor                        | 240V   | HP                                    | 10                                     |
|                                   | for three-phase motor                        | 240V<br>480V                                       | HP<br>HP                              | 10<br>15                               |
|                                   |  | 240V<br>480V                                       | HP<br>HP                              | 10<br>15                               |
|                                   |  | 240V<br>480V<br>600V                               | HP<br>HP<br>HP                        | 10<br>15<br>15                         |
| Ambient conditions                |  | 240V<br>480V<br>600V<br>120V                       | HP<br>HP<br>HP                        | 10<br>15<br>15<br>2                    |
| Ambient conditions<br>Temperature | for single-phase motor                       | 240V<br>480V<br>600V<br>120V                       | HP<br>HP<br>HP                        | 10<br>15<br>15<br>2                    |
|                                   |  | 240V<br>480V<br>600V<br>120V<br>240V               | HP<br>HP<br>HP<br>HP                  | 10<br>15<br>15<br>2<br>5               |
|                                   | for single-phase motor                       | 240V<br>480V<br>600V<br>120V                       | HP<br>HP<br>HP<br>HP                  | 10<br>15<br>15<br>2<br>5<br>-25        |
|                                   | for single-phase motor Operating temperature | 240V<br>480V<br>600V<br>120V<br>240V               | HP<br>HP<br>HP<br>HP                  | 10<br>15<br>15<br>2<br>5               |
|                                   | for single-phase motor                       | 240V<br>480V<br>600V<br>120V<br>240V<br>min<br>max | HP<br>HP<br>HP<br>HP<br>HP<br>C<br>°C | 10<br>15<br>15<br>2<br>5<br>-25<br>+55 |
|                                   | for single-phase motor Operating temperature | 240V<br>480V<br>600V<br>120V<br>240V<br>min        | HP<br>HP<br>HP<br>HP                  | 10<br>15<br>15<br>2<br>5<br>-25        |


GX40136U


The characteristics described in this document are subject to updates or modifications at any time. The descriptions, technical and functional information, illustrations and instructions in this brochure are purely illustrative, and are consequently not contractually binding



## GX40136U ROTARY CAM SWITCH GX SERIES, MULTI-STEP 0-1-2-3, 3 POLES 40A, FOR FRONT MOUNTING WITH BLACK HANDLE, FRONT PLATE 65X65MM








Drillings for 4 screws fixing (4V version).

| Series | Dimensions |      |     |     |      |    | L Number of elements |    |      |    |      |    |      |     |       |     |       |     |       |
|--------|------------|------|-----|-----|------|----|----------------------|----|------|----|------|----|------|-----|-------|-----|-------|-----|-------|
| Selles | □A         | С    | ØD1 | ØD2 | E    | □K | ۵N                   | 1  | 2    | 3  | 4    | 5  | 6    | 7   | 8     | 9   | 10    | 11  | 12    |
| GX16   | 48         | 39.5 | 12  | 5   | 26.5 | 36 | 6                    | 43 | 51.5 | 60 | 68.5 | 77 | 85.5 | 94  | 102.5 | 111 | 119.5 | 128 | 136.5 |
| GX20   | 48         | 39.5 | 12  | 5   | 26.5 | 36 | 6                    | 43 | 51.5 | 60 | 68.5 | 77 | 85.5 | 94  | 102.5 | 111 | 119.5 | 128 | 136.5 |
| GX32   | 65         | 53   | 14  | 5   | 34.5 | 48 | 7                    | 51 | 63   | 75 | 85   | 99 | 111  | 123 | 135   | 147 | 159   | 171 | 183   |
| GX40   | 65         | 53   | 14  | 5   | 34.5 | 48 | 7                    | 51 | 63   | 75 | 85   | 99 | 111  | 123 | 135   | 147 | 159   | 171 | 183   |

### Wiring diagrams



# Certifications and compliance

#### Compliance

| -                   | CSA C22.2 n° 14     |  |
|---------------------|---------------------|--|
|                     | IEC/EN/BS 60947-1   |  |
|                     | IEC/EN/BS 60947-3   |  |
|                     | IEC/EN/BS 60947-5-1 |  |
|                     | IEC/EN/BS 61058-1   |  |
|                     | UL60947-4-1         |  |
| Certificates        |                     |  |
|                     | cULus               |  |
|                     | EAC                 |  |
| ETIM classification |                     |  |
| ETIM 8.0            |                     | EC001029 -<br>Selector switch,<br>complete |

complete