

## ROTARY CAM SWITCH 7GN SERIES, 1-PHASE MOTOR REVERSING SWITCH WITH SPRING RETURN 16A, FOR FRONT MOUNTING WITH BLACK HANDLE, FRONT PLATE 48X48MM

Product designation			Rotary cam switches
Product type designation			7GN12
General characteristics			05 4 mh
Switching diagram			25 - 1-phase motor reversing switch with spring return
N° of elements			2
Mounting form			U - Front mounting with black handle
Contact characteristics			
Rated insulation voltage Ui			
	IEC/EN	V	690
	UL/CSA	V	600
Rated impulse withstand voltage Uimp		kV	6
Conventional free air thermal current Ith			
	IEC/EN	Α	16
	UL/CSA	Α	15
Rated operational voltage		V	480
Rated operational impulse voltage		kV	4
Maximum fuse size for short-circuit protection In (gG)			
	10kA	Α	16
	15kA	A	10
Detect of the set time a suggest law.	25kA	Α	10
Rated short time current Icw	4.5	LεΛ	200
Conductivity	1s	kA	200 10/5 mA/V
Conductivity Operational current le IEC/EN			10/3 IIIA/ V
AC1/AC21A			
ACT/ACZTA		Α	16
AC15			10
7.010	110V	Α	10
	220/230V	Α	8
	380/400V	Α	4
	660/690V	Α	1.5
Rated operational power in AC			_
Three-phase AC-3			
	220/230V	kW	2.5
	380/440V	kW	4
	500/690V	kW	5.5
Single-phase AC-3			
	110V	kW	0.8
	220/230V	kW	1.5
	380/440V	kW	2.2
Three-phase AC23A	000/000		•
	220/230V	kW	3
	380/440V	kW	5.5
O:I A000A	500/690V	kW	7.5
Single-phase AC23A	44017	1-147	0.0
	110V 220/230V	kW kW	0.8 1.7
	380/440V	kW	3
	300/440V	IX V V	

**ENERGY AND AUTOMATION** 

## ROTARY CAM SWITCH 7GN SERIES, 1-PHASE MOTOR REVERSING SWITCH WITH SPRING RETURN 16A, FOR FRONT MOUNTING WITH BLACK HANDLE, FRONT PLATE 48X48MM


Rated operational c				
	DC21A			
		48V	Α	12
		60V	Α	12
		110V	Α	4
		220V	Α	0.6
		440V	Α	0.25
	DC23A (poles in series)	1101	- / (	0.20
	DC23A (poles ili selles)	24V	۸	10 (1)
		48V	A	10 (1)
			A	10 (2)
		60V	Α	10 (3)
		110V	Α	5 (3)
		220V	Α	5 (4)
	DC13			
		24V	Α	12
		48V	Α	10
		60V	Α	8
		110V	Α	1
		220V	Α	0.4
		440V	A	0.15
Power dissipation		7701	W	0.8
Mechanical features	<u> </u>		V V	0.0
Terminals screw				M3
	er terminale may		Nm	
Tightening torque fo	ir terminais max		INIII	0.5
Conductor size				
	AWG - Rigid cable	_		
		min	AWG	20
		Max	AWG	12
	AWG - Flexible cable			
		min	AWG	20
		Max	AWG	14
	Conductor size (IEC) - Flexible cable			
		min	mm²	0.5
		Max	mm²	2.5
	Conductor size (IEC) - Rigid cable			
		min	mm²	0.5
		Max	mm²	2.5
Mechanical life		IVICA	cycles	3x10 <sup>6</sup>
UL technical data			Cycles	JA 10
Motor power for dire	ect-on-line control			
Motor Power for diff				
	for three-phase motor	4001/	ווס	1 E
		120V	HP	1.5
		240V	HP	3
	for single-phase motor			
		120V	HP	0.5
		240V	HP	1
Ambient conditions				
Temperature				
	Operating temperature			
		min	°C	-25
		max	°C	+55
	Storage temperature			
	3 1	min	°C	-40
		max	°C	+70
		· · · · · · · · · · · · · · · · · · ·		· · · ·

**ENERGY AND AUTOMATION** 

ROTARY CAM SWITCH 7GN SERIES, 1-PHASE MOTOR REVERSING SWITCH WITH SPRING RETURN 16A, FOR FRONT MOUNTING WITH BLACK HANDLE, FRONT PLATE 48X48MM


# Resistance & Protection Frontal IP degree IP40 Terminals IP degree IP00

#### **Dimensions**



Series	Dimensions									L Number of elements											
	□A	С	ØD	ØD1	ØD2	Е	ØG	□K	□N	1	2	3	4	5	6	7	8	9	10	11	12
7GN12	48	39.5	39	12	5	26.5	38	36	6	36.1	45.8	55.5	65.2	74.9	84.6	94.3	104	113.7	123.4	133.1	142.8
7GN20	48	39.5	39	12	5	26.5	38	36	6	36.1	45.8	55.5	65.2	74.9	84.6	94.3	104	113.7	123.4	133.1	142.8
7GN25	48	39.5	43	12	5	26.5	38	36	6	40.5	54.1	67.7	81.3	94.9	108.5	122.1	135.7	147.3	162.9	176.5	190.1
7GN32	65	53	58	14	5	34.5	58.5	48	7	46.5	61.6	76.7	91.8	106.9	122	137.1	152.2	167.3	182.4	197.5	212.6
7GN40	65	53	58	14	5	34.5	58.5	48	7	46.5	61.6	76.7	91.8	106.9	122	137.1	152.2	167.3	182.4	197.5	212.6
7GN63	65	53	62	14	5	34.5	58.5	48	7	50.3	68.4	86.5	104.6	122.7	140.8	158.9	177	195.1	213.2	231.3	249.4
7GN125	90	70.5	86	16	6	41.5	84	68	9	67.3	96.4	125.5	154.6	183.7	220.3	249.4	278.5	307.6	336.7	365.8	394.9

### Wiring diagrams



#### Certifications and compliance

Compliance

CSA C22.2 n° 14

IEC/EN/BS 60947-1

IEC/EN/BS 60947-3

IEC/EN/BS 60947-5-1

UL60947-4-1

Certificates

cCSAus

EAC

UL

ETIM classification

**ETIM 8.0** 

EC001029 -Selector switch, complete