



# ROTARY CAM SWITCH 7GN SERIES, MULTI-STEP 1-2-3-4, 1 POLE 20A, FOR FRONT MOUNTING WITH BLACK HANDLE, FRONT PLATE 48X48MM

Product designation				Rotary cam
_				switches
Product type designat General characteristic				7GN20
Switching diagram	3			83 - Multi-step 1- 2-3-4 1 pole
N° of elements				2
Mounting form				U - Front mounting with black handle
Contact characteristics	S			
Rated insulation voltage	ge Ui			
		IEC/EN	V	690
		UL/CSA	V	600
Rated impulse withsta	• •		kV	6
Conventional free air t	nermal current Ith	IEO/EN	Δ.	00
		IEC/EN UL/CSA	A A	20 20
Rated operational volt	200	UL/CSA		480
Rated operational imp			kV	4
	r short-circuit protection In (gG)		ic v	
Waxiiiiaiii 1000 0120 10	r short should protostion in (ge)	10kA	Α	20
		15kA	Α	16
		25kA	Α	16
Rated short time curre	ent Icw			·
		1s	kA	250
Conductivity				10/5 mA/V
Operational current le	IEC/EN			
	AC1/AC21A			
			Α	20
	AC15	440)/	•	4.0
		110V 220/230V	A	10
		380/400V	A A	8 6
		660/690V	A	1.5
Rated operational pow	ver in AC	000/030 V		1.0
tatoa oporational por	Three-phase AC-3			
		220/230V	kW	3
		380/440V	kW	5.5
		500/690V	kW	5.5
	Single-phase AC-3			
		110V	kW	0.8
		220/230V	kW	2.2
	<del>-</del>	380/440V	kW	3
	Three-phase AC23A	000/0001	1.3.67	F
		220/230V	kW	5
		380/440V 500/690V	kW kW	7.5 7.5
	Single-phase AC23A	300/0907	r v v	1.0
	Single-phase AUZUA	110V	kW	0.8
		220/230V	kW	2.5
		380/440V	kW	3.7
Rated operational curr	rent in DC			






# ROTARY CAM SWITCH 7GN SERIES, MULTI-STEP 1-2-3-4, 1 POLE 20A, FOR FRONT MOUNTING WITH BLACK HANDLE, FRONT PLATE 48X48MM


	DC21A				
	DOZTA	48V	Α	20	
		60V	A	20	
		110V	A	4	
		220V	A	0.6	
		440V	A	0.25	
	DC23A (poles in series)	7701		0.20	
	20207 (poice in conce)	24V	Α	20 (1)	
		48V	A	20 (2)	
		60V	A	20 (3)	
		110V	A	10 (3)	
		220V	A	8 (4)	
	DC13	2201		0 (1)	
	2010	24V	Α	20	
		48V	Α	16	
		60V	A	12	
		110V	A	1	
		220V	A	0.4	
		440V		0.4	
Power dissipation		440 V	— A W	0.15	
Mechanical features			VV	0.6	
Terminals screw				M3	
Tightening torque for te	arminals may		Nm	0.5	
Conductor size	errillias max		INIII	0.5	
Conductor Size	AWG - Rigid cable				
	AVVG - Rigid Cable	min	AWG	20	
		Max	AWG	12	
	AWG - Flexible cable	IVIAX	AWG	12	
	AVVG - Flexible cable		A1A/C	20	
		min	AWG	20	
		N/a			
	Conductor size (IFC) Florible coble	Max	AWG	14	
	Conductor size (IEC) - Flexible cable				
	Conductor size (IEC) - Flexible cable	min	mm²	0.5	
	Conductor size (IEC) - Flexible cable  Conductor size (IEC) - Rigid cable	min Max	mm² mm²	0.5 2.5	
		min Max min	mm² mm²	0.5 2.5 0.5	
Machaniaellife		min Max	mm² mm² mm² mm²	0.5 2.5 0.5 2.5	
Mechanical life		min Max min	mm² mm²	0.5 2.5 0.5	_
UL technical data	Conductor size (IEC) - Rigid cable	min Max min	mm² mm² mm² mm²	0.5 2.5 0.5 2.5	
	Conductor size (IEC) - Rigid cable	min Max min	mm² mm² mm² mm²	0.5 2.5 0.5 2.5	
UL technical data	Conductor size (IEC) - Rigid cable	min Max min Max	mm² mm² mm² mm² cycles	0.5 2.5 0.5 2.5 5x10 <sup>6</sup>	
UL technical data	Conductor size (IEC) - Rigid cable	min Max min Max	mm² mm² mm² mm² cycles	0.5 2.5 0.5 2.5 5x10 <sup>6</sup>	_
UL technical data	Conductor size (IEC) - Rigid cable	min Max min Max 120V 240V	mm² mm² mm² cycles	0.5 2.5 0.5 2.5 5x10 <sup>6</sup>	_
UL technical data	Conductor size (IEC) - Rigid cable	min Max min Max 120V 240V 480V	mm² mm² mm² cycles	0.5 2.5 0.5 2.5 5x10 <sup>6</sup> 1.5 3 7.5	_
UL technical data	Conductor size (IEC) - Rigid cable on-line control for three-phase motor	min Max min Max 120V 240V	mm² mm² mm² cycles	0.5 2.5 0.5 2.5 5x10 <sup>6</sup>	
UL technical data	Conductor size (IEC) - Rigid cable	min Max min Max 120V 240V 480V 600V	mm² mm² mm² cycles	0.5 2.5 0.5 2.5 5x10 <sup>6</sup> 1.5 3 7.5	
UL technical data	Conductor size (IEC) - Rigid cable on-line control for three-phase motor	min Max min Max 120V 240V 480V 600V	mm² mm² mm² cycles	0.5 2.5 0.5 2.5 5x10 <sup>6</sup> 1.5 3 7.5 10	
UL technical data Motor power for direct-	Conductor size (IEC) - Rigid cable on-line control for three-phase motor	min Max min Max 120V 240V 480V 600V	mm² mm² mm² cycles	0.5 2.5 0.5 2.5 5x10 <sup>6</sup> 1.5 3 7.5	
UL technical data Motor power for direct-	Conductor size (IEC) - Rigid cable on-line control for three-phase motor	min Max min Max 120V 240V 480V 600V	mm² mm² mm² cycles	0.5 2.5 0.5 2.5 5x10 <sup>6</sup> 1.5 3 7.5 10	
UL technical data Motor power for direct-	Conductor size (IEC) - Rigid cable  on-line control for three-phase motor  for single-phase motor	min Max min Max 120V 240V 480V 600V	mm² mm² mm² cycles	0.5 2.5 0.5 2.5 5x10 <sup>6</sup> 1.5 3 7.5 10	
UL technical data Motor power for direct-	Conductor size (IEC) - Rigid cable on-line control for three-phase motor	min Max min Max 120V 240V 480V 600V 120V 240V	mm² mm² mm² cycles	0.5 2.5 0.5 2.5 5x10 <sup>6</sup> 1.5 3 7.5 10	
UL technical data Motor power for direct-	Conductor size (IEC) - Rigid cable  on-line control for three-phase motor  for single-phase motor	min Max min Max 120V 240V 480V 600V 120V 240V	mm² mm² mm² cycles  HP HP HP HP HP	0.5 2.5 0.5 2.5 5x10 <sup>6</sup> 1.5 3 7.5 10	
UL technical data Motor power for direct-	Conductor size (IEC) - Rigid cable  on-line control for three-phase motor  for single-phase motor  Operating temperature	min Max min Max 120V 240V 480V 600V 120V 240V	mm² mm² mm² cycles	0.5 2.5 0.5 2.5 5x10 <sup>6</sup> 1.5 3 7.5 10	
UL technical data Motor power for direct-	Conductor size (IEC) - Rigid cable  on-line control for three-phase motor  for single-phase motor	min Max min Max 120V 240V 480V 600V 120V 240V	mm² mm² mm² cycles  HP HP HP HP HP	0.5 2.5 0.5 2.5 5x10 <sup>6</sup> 1.5 3 7.5 10	



## ROTARY CAM SWITCH 7GN SERIES, MULTI-STEP 1-2-3-4, 1 POLE 20A, FOR FRONT MOUNTING WITH BLACK HANDLE, FRONT PLATE 48X48MM

	max	°C	+70
Resistance & Protection			
Frontal IP degree			IP40
Terminals IP degree			IP00
Dimensions			






Standard drillings for 7GN125. Drillings on request for 4 screws fixing (4V version).

Series	Dimensions								L Number of elements												
Series	ΠA	С	ØD	ØD1	ØD2	Е	ØG	□K	□N	1	2	3	4	5	6	7	8	9	10	11	12
7GN12	48	39.5	39	12	5	26.5	38	36	6	36.1	45.8	55.5	65.2	74.9	84.6	94.3	104	113.7	123.4	133.1	142.8
7GN20	48	39.5	39	12	5	26.5	38	36	6	36.1	45.8	55.5	65.2	74.9	84.6	94.3	104	113.7	123.4	133.1	142.8
7GN25	48	39.5	43	12	5	26.5	38	36	6	40.5	54.1	67.7	81.3	94.9	108.5	122.1	135.7	147.3	162.9	176.5	190.1
7GN32	65	53	58	14	5	34.5	58.5	48	7	46.5	61.6	76.7	91.8	106.9	122	137.1	152.2	167.3	182.4	197.5	212.6
7GN40	65	53	58	14	5	34.5	58.5	48	7	46.5	61.6	76.7	91.8	106.9	122	137.1	152.2	167.3	182.4	197.5	212.6
7GN63	65	53	62	14	5	34.5	58.5	48	7	50.3	68.4	86.5	104.6	122.7	140.8	158.9	177	195.1	213.2	231.3	249.4
7GN125	90	70.5	86	16	6	41.5	84	68	9	67.3	96.4	125.5	154.6	183.7	220.3	249.4	278.5	307.6	336.7	365.8	394.9

#### Wiring diagrams



### Certifications and compliance

Compliance

CSA C22.2 n° 14

IEC/EN/BS 60947-1

IEC/EN/BS 60947-3

IEC/EN/BS 60947-5-1

UL60947-4-1

Certificates

cCSAus

EAC

UL

ETIM classification

ETIM 8.0

EC001029 -Selector switch, complete