



ROTARY CAM SWITCH 7GN SERIES, CHANGEOVER SWITCH WITHOUT 0, 4 POLES 32A, FOR FRONT MOUNTING WITH BLACK HANDLE, FRONT PLATE 65X65MM

Product designation			Rotary cam switches
Product type designation			7GN32
General characteristics			69 - Changeover
Switching diagram			switch without 0 4 poles
N° of elements			4
Mounting form			U - Front mounting with black handle
Contact characteristics			
Rated insulation voltage Ui			
	IEC/EN	V	690
	UL/CSA	V	600
Rated impulse withstand voltage Uimp		kV	6
Conventional free air thermal current Ith			
	IEC/EN	Α	32
	UL/CSA	Α	40
Rated operational voltage		V	480
Rated operational impulse voltage		kV	4
Maximum fuse size for short-circuit protection In (gG)			
	10kA	Α	32
	15kA	Α	32
	25kA	Α	32
	50kA	A	32
Rated short time current lcw			
0.1.00	1s	kA	800
Conductivity			10/5 mA/V
Operational current le IEC/EN			
AC1/AC21A		Α	32
AC15			32
A013	110V	Α	25
	220/230V	A	20
	380/400V	A	10
	660/690V	A	2
Rated operational power in AC	330,000 V		-
Three-phase AC-3			
	220/230V	kW	7.5
	380/440V	kW	11
	500/690V	kW	11
Single-phase AC-3			
5 ,	110V	kW	2.2
	220/230V	kW	4
	380/440V	kW	6.5
Three-phase AC23A			
	220/230V	kW	8
	380/440V	kW	15
	500/690V	kW	18.5
Single-phase AC23A			
	110V	kW	2.2
	220/230V	kW	4
	380/440V	kW	7.5

ROTARY CAM SWITCH 7GN SERIES, CHANGEOVER SWITCH WITHOUT 0, 4 POLES 32A, FOR FRONT MOUNTING WITH BLACK HANDLE, FRONT PLATE 65X65MM


Rated operational current in DC DC21A 48V A 32 60V A 32 110V A 6	
48V A 32 60V A 32	
60V A 32	
	2
110\/	2
110V A 6	
	9
DC23A (poles in series)	
24V A 32	2 (1)
48V A 32	2 (2)
60V A 32	2 (3)
110V A 15	5 (3)
220V A 12	2 (4)
DC13	
24V A 32	2
48V A 25	5
60V A 16	5
110V A 3	
220V A 0.	5
Power dissipation W 1.	5
Mechanical features	
Terminals screw M	4
Tightening torque for terminals max Nm 1.	2
Conductor size	
AWG - Rigid cable	
min AWG 16	6
Max AWG 8	
AWG - Flexible cable	
min AWG 16	6
Max AWG 10	
Conductor size (IEC) - Flexible cable	
min mm² 1.	5
Max mm ² 4	
Conductor size (IEC) - Rigid cable	
min mm² 1.	5
Max mm ² 6	
	:10 ⁶
JL technical data	_
Motor power for direct-on-line control	
VIOLOI DOMOI IUI UII CUI III IU CUI III III III III	
·	
for three-phase motor)
for three-phase motor 120V HP 5	
for three-phase motor 120V HP 5 240V HP 10	
for three-phase motor 120V HP 5 240V HP 10 480V HP 15	5
for three-phase motor 120V HP 5 240V HP 10 480V HP 15 600V HP 15	5
for three-phase motor 120V HP 5 240V HP 10 480V HP 15 600V HP 15	5
for three-phase motor 120V HP 5 240V HP 10 480V HP 15 600V HP 15 for single-phase motor 120V HP 2	5
for three-phase motor 120V HP 5 240V HP 10 480V HP 15 600V HP 15 for single-phase motor 120V HP 2 240V HP 5	5
for three-phase motor 120V	5
for three-phase motor 120V HP 5 240V HP 10 480V HP 15 600V HP 15 for single-phase motor 120V HP 2 240V HP 5 Ambient conditions Temperature Operating temperature min °C -2 max °C +5	5
for three-phase motor 120V	5 5 5 5 5 5
for three-phase motor 120V HP 5 240V HP 10 480V HP 15 600V HP 15 for single-phase motor 120V HP 2 240V HP 5 Ambient conditions Temperature Operating temperature min °C -2 max °C +5	5 5 5 5 5 5 5 0


ENERGY AND AUTOMATION

ROTARY CAM SWITCH 7GN SERIES, CHANGEOVER SWITCH WITHOUT 0, 4 POLES 32A, FOR FRONT MOUNTING WITH BLACK HANDLE, FRONT PLATE 65X65MM

Resistance & Protection Frontal IP degree IP40 Terminals IP degree IP00

Dimensions






Standard drillings for 7GN125.

Drillings on request for 4 screws fixing (4V version).

Series	Dimensions								L Number of elements												
	ΠA	С	ØD	ØD1	ØD2	Е	ØG	□K	□N	1	2	3	4	5	6	7	8	9	10	11	12
7GN12	48	39.5	39	12	5	26.5	38	36	6	36.1	45.8	55.5	65.2	74.9	84.6	94.3	104	113.7	123.4	133.1	142.8
7GN20	48	39.5	39	12	5	26.5	38	36	6	36.1	45.8	55.5	65.2	74.9	84.6	94.3	104	113.7	123.4	133.1	142.8
7GN25	48	39.5	43	12	5	26.5	38	36	6	40.5	54.1	67.7	81.3	94.9	108.5	122.1	135.7	147.3	162.9	176.5	190.1
7GN32	65	53	58	14	5	34.5	58.5	48	7	46.5	61.6	76.7	91.8	106.9	122	137.1	152.2	167.3	182.4	197.5	212.6
7GN40	65	53	58	14	5	34.5	58.5	48	7	46.5	61.6	76.7	91.8	106.9	122	137.1	152.2	167.3	182.4	197.5	212.6
7GN63	65	53	62	14	5	34.5	58.5	48	7	50.3	68.4	86.5	104.6	122.7	140.8	158.9	177	195.1	213.2	231.3	249.4
7GN125	90	70.5	86	16	6	41.5	84	68	9	67.3	96.4	125.5	154.6	183.7	220.3	249.4	278.5	307.6	336.7	365.8	394.9

Wiring diagrams



Certifications and compliance

Compliance

CSA C22.2 n° 14

IEC/EN/BS 60947-1

IEC/EN/BS 60947-3

IEC/EN/BS 60947-5-1

UL60947-4-1

Certificates

cCSAus

EAC

UL

ETIM classification

ETIM 8.0

EC001029 -Selector switch, complete