ROTARY CAM SWITCH GX SERIES, CHANGEOVER SWITCH WITHOUT 0, 1 POLE 16A, FOR FRONT MOUNTING WITH BLACK HANDLE, FRONT PLATE 48X48MM

B 1 1 1 1 1 1				Rotary cam
Product designation				switches
Product type designation				GX16
General characteristics				54 - Changeover
Switching diagram				switch without 0 1
N° of elements				1
				U - Front
Mounting form				mounting with black handle
Contact characteristics				black handle
Rated insulation voltag				
		IEC/EN	V	690
		UL/CSA	V	600
Rated impulse withstar	nd voltage Uimp		kV	6
Conventional free air th				
		IEC/EN	Α	16
		UL/CSA	Α	12
Rated operational volta	nge		V	440
Rated operational impu	ulse voltage		kV	4
Maximum fuse size for	short-circuit protection In (gG)			
		10kA	Α	16
		15kA	Α	16
		25kA	Α	16
Rated short time curre	nt Icw			
		1s	kA	250
Conductivity				10/5 mA/V
Operational current le	IEC/EN			
	AC1/AC21A			
			Α	16
	AC15			
		110V	Α	10
		220/230V	Α	8
		380/400V	A	4
Detailerendenden		660/690V	Α	1.5
Rated operational pow				
	Three-phase AC-3	220/2201/	1.1.1.1	2.5
		220/230V 380/440V	kW kW	3.5 4.5
		500/440V 500/690V	kW	5.5
	Single-phase AC-3	300/090 V	N V V	<u> </u>
	Single-phase AC-3	110V	kW	0.55
		220/230V	kW	1.5
		380/440V	kW	2.2
	Three-phase AC23A	330,1101		
	7.1.00 p.1.000 7.10207	220/230V	kW	3.7
		380/440V	kW	6.5
		500/690V	kW	7.5
	Single-phase AC23A			
		110V	kW	0.75
		220/230V	kW	1.8
		380/440V	kW	3
Rated operational curre	ent in DC			




ROTARY CAM SWITCH GX SERIES, CHANGEOVER SWITCH WITHOUT 0, 1 POLE 16A, FOR FRONT MOUNTING WITH BLACK HANDLE, FRONT PLATE 48X48MM


	DC21A			
	DCZTA	48V	Α	16
		60V	A	16
		110V	A	4
		220V	A	0.6
		440V	A	0.25
	DC23A (poles in series)	440 V		0.23
	DOZON (poles in series)	24V	Α	16 (1)
		48V	A	16 (2)
		60V	A	16 (3)
		110V	A	10 (3)
		220V	Α	7 (4)
	DC13			. (.)
		24V	Α	16
		48V	Α	14
		60V	Α	10
		110V	Α	1
		220V	Α	0.4
		440V	Α	0.15
Power dissipation			W	0.6
Mechanical features				
Terminals screw				3M
Tightening torque for te	erminals max		Nm	0.5
Conductor size				
	AWG - Rigid cable			
	3	min	AWG	20
		Max	AWG	12
	AWG - Flexible cable			
				00
		min	AWG	20
		min Max	AWG AWG	12
	Conductor size (IEC) - Flexible cable			
	Conductor size (IEC) - Flexible cable			
	Conductor size (IEC) - Flexible cable	Max	AWG	12
	Conductor size (IEC) - Flexible cable Conductor size (IEC) - Rigid cable	Max min	AWG	0.5
		Max min	AWG	0.5
		Max min Max	AWG mm² mm²	12 0.5 2.5
Mechanical life		Max min Max min	AWG mm² mm² mm²	0.5 2.5 0.5
UL technical data	Conductor size (IEC) - Rigid cable	Max min Max min	AWG mm² mm² mm² mm²	0.5 2.5 0.5 2.5
	Conductor size (IEC) - Rigid cable	Max min Max min	AWG mm² mm² mm² mm²	0.5 2.5 0.5 2.5
UL technical data	Conductor size (IEC) - Rigid cable	Max min Max min Max	AWG mm² mm² mm² cycles	0.5 2.5 0.5 2.5 1X10 ⁶
UL technical data	Conductor size (IEC) - Rigid cable	Max min Max min Max	AWG mm² mm² mm² cycles	12 0.5 2.5 0.5 2.5 1X10 ⁶
UL technical data	Conductor size (IEC) - Rigid cable	Max min Max min Max	AWG mm² mm² mm² cycles HP HP	12 0.5 2.5 0.5 2.5 1X10 ⁶ 1.5 3
UL technical data	Conductor size (IEC) - Rigid cable	Max min Max min Max 120V 240V 480V	AWG mm² mm² mm² cycles HP HP	12 0.5 2.5 0.5 2.5 1X10 ⁶ 1.5 3 5
UL technical data	Conductor size (IEC) - Rigid cable -on-line control for three-phase motor	Max min Max min Max	AWG mm² mm² mm² cycles HP HP	12 0.5 2.5 0.5 2.5 1X10 ⁶ 1.5 3
UL technical data	Conductor size (IEC) - Rigid cable	Max min Max min Max 120V 240V 480V 600V	AWG mm² mm² mm² cycles HP HP HP	12 0.5 2.5 0.5 2.5 1X10 ⁶ 1.5 3 5 5
UL technical data	Conductor size (IEC) - Rigid cable -on-line control for three-phase motor	Max min Max min Max 120V 240V 480V 600V	AWG mm² mm² mm² cycles HP HP HP HP	12 0.5 2.5 0.5 2.5 1X10° 1.5 3 5 5
UL technical data Motor power for direct-	Conductor size (IEC) - Rigid cable -on-line control for three-phase motor	Max min Max min Max 120V 240V 480V 600V	AWG mm² mm² mm² cycles HP HP HP	12 0.5 2.5 0.5 2.5 1X10 ⁶ 1.5 3 5 5
UL technical data Motor power for direct-	Conductor size (IEC) - Rigid cable -on-line control for three-phase motor	Max min Max min Max 120V 240V 480V 600V	AWG mm² mm² mm² cycles HP HP HP HP	12 0.5 2.5 0.5 2.5 1X10° 1.5 3 5 5
UL technical data Motor power for direct-	Conductor size (IEC) - Rigid cable -on-line control for three-phase motor for single-phase motor	Max min Max min Max 120V 240V 480V 600V	AWG mm² mm² mm² cycles HP HP HP HP	12 0.5 2.5 0.5 2.5 1X10° 1.5 3 5 5
UL technical data Motor power for direct-	Conductor size (IEC) - Rigid cable -on-line control for three-phase motor	Max min Max min Max 120V 240V 480V 600V 120V 240V	AWG mm² mm² mm² cycles HP HP HP HP	12 0.5 2.5 0.5 2.5 1X10 ⁶ 1.5 3 5 5
UL technical data Motor power for direct-	Conductor size (IEC) - Rigid cable -on-line control for three-phase motor for single-phase motor	Max min Max min Max 120V 240V 480V 600V 120V 240V	AWG mm² mm² mm² cycles HP HP HP HP HP HP	12 0.5 2.5 0.5 2.5 1X10 ⁶ 1.5 3 5 5 0.75 1
UL technical data Motor power for direct-	Conductor size (IEC) - Rigid cable -on-line control for three-phase motor for single-phase motor Operating temperature	Max min Max min Max 120V 240V 480V 600V 120V 240V	AWG mm² mm² mm² cycles HP HP HP HP	12 0.5 2.5 0.5 2.5 1X10 ⁶ 1.5 3 5 5
UL technical data Motor power for direct-	Conductor size (IEC) - Rigid cable -on-line control for three-phase motor for single-phase motor	Max min Max min Max 120V 240V 480V 600V 120V 240V	AWG mm² mm² mm² cycles HP HP HP HP HP HP	12 0.5 2.5 0.5 2.5 1X10 ⁶ 1.5 3 5 5 0.75 1

ENERGY AND AUTOMATION

ROTARY CAM SWITCH GX SERIES, CHANGEOVER SWITCH WITHOUT 0, 1 POLE 16A, FOR FRONT MOUNTING WITH BLACK HANDLE, FRONT PLATE 48X48MM

	max	°C	+70
Resistance & Protection			
Frontal IP degree			IP65
Terminals IP degree			IP20
Dimensions			






Drillings for 4 screws fixing (4V version).

Series -	Dimensions							L Number of elements											
	□A	C	ØD1	ØD2	Е	□K	□N	1	2	3	4	5	6	7	8	9	10	11	12
GX16	48	39.5	12	5	26.5	36	6	43	51.5	60	68.5	77	85.5	94	102.5	111	119.5	128	136.5
GX20	48	39.5	12	5	26.5	36	6	43	51.5	60	68.5	77	85.5	94	102.5	111	119.5	128	136.5
GX32	65	53	14	5	34.5	48	7	51	63	75	85	99	111	123	135	147	159	171	183
GX40	65	53	14	5	34.5	48	7	51	63	75	85	99	111	123	135	147	159	171	183

Wiring diagrams



Certifications and compliance

Compliance

CSA C22.2 n° 14

IEC/EN/BS 60947-1

IEC/EN/BS 60947-3

IEC/EN/BS 60947-5-1

IEC/EN/BS 61058-1 UL60947-4-1

Certificates

cULus

EAC

ETIM classification

ETIM 8.0

EC001105 - Offload switch