

## ROTARY CAM SWITCH GX SERIES, CHANGEOVER SWITCH 1 POLE 32A, FOR FRONT MOUNTING WITH BLACK HANDLE, FRONT PLATE 65X65MM

Product designation			Rotary cam switches
Product type designation			GX32
General characteristics			
Switching diagram			51 - Changeover switch 1 pole
N° of elements			1
Mounting form			U - Front mounting with black handle
Contact characteristics			Sidor Harraro
Rated insulation voltage Ui			
	IEC/EN	V	690
	UL/CSA	V	600
Rated impulse withstand voltage Uimp		kV	6
Conventional free air thermal current Ith	IEO/EN	Δ.	00
	IEC/EN UL/CSA	A A	32 32
Rated operational voltage	OLICOA	$\frac{\lambda}{V}$	440
Rated operational impulse voltage		kV	4
Maximum fuse size for short-circuit protection In (gG)			·
,	10kA	Α	35
	15kA	Α	35
	25kA	Α	35
Rated short time current lcw			
	1s	kA	1000
Conductivity			10/5 mA/V
Operational current le IEC/EN AC1/AC21A			
ACT/ACZTA		Α	32
AC15			32
7.010	110V	Α	25
	220/230V	Α	20
	380/400V	Α	10
	660/690V	Α	2
Rated operational power in AC			
Three-phase AC-3	000/000/		
	220/230V	kW	7.5
	380/440V 500/690V	kW kW	11 11
Single-phase AC-3	300/090 V	KVV	11
Single-phase AC-3	110V	kW	1.8
	220/230V	kW	3.5
	380/440V	kW	5.5
Three-phase AC23A			
	220/230V	kW	8
	380/440V	kW	15
<del></del>	500/690V	kW	15
Single-phase AC23A	4401	1 147	0.0
	110V	kW	2.2
	220/230V 380/440V	kW kW	3.5 6
Rated operational current in DC	360/440 V	KVV	0




## ROTARY CAM SWITCH GX SERIES, CHANGEOVER SWITCH 1 POLE 32A, FOR FRONT MOUNTING WITH BLACK HANDLE, FRONT PLATE 65X65MM


	DC21A			
	DCZTA	48V	Α	32
		60V	A	32
		110V	A	5
		220V	A	0.8
		440V	A	0.25
	DC23A (poles in series)	440 V		0.23
	DOZDA (poles in series)	24V	Α	32 (1)
		48V	A	32 (2)
		60V	A	32 (3)
		110V	A	15 (3)
		220V	Α	12 (4)
	DC13			. = ( . /
		24V	Α	32
		48V	Α	25
		60V	Α	14
		110V	Α	3
		220V	A	0.5
		440V	Α	0.15
Power dissipation			W	1.6
Mechanical features				
Terminals screw				M4
Tightening torque for te	rminals max		Nm	1.2
Conductor size				
	AWG - Rigid cable			
	•	min	AWG	16
		Max	AWG	8
	AWG - Flexible cable			
		min	AWG	16
		Max	AWG	10
	Conductor size (IEC) - Flexible cable			
		min	mm²	1.5
		Max	mm²	6
	Conductor size (IEC) - Rigid cable			
		min	mm²	1.5
		Max	mm²	10
Mechanical life			cycles	1X10 <sup>6</sup>
UL technical data				
Motor power for direct-				
	for three-phase motor			
		120V	HP	3
		240V	HP	7.5
		480V	HP	15
		600V	HP	15
	for single-phase motor			
	5 .			
	<b>5</b> ,	120V	HP	1.5
A I I I I I I I I I I I I I I I I I I I	<b>5</b> 1	120V 240V	HP HP	3
Ambient conditions				
Ambient conditions Temperature				
	Operating temperature	240V	HP	3
		240V min	HP °C	-25
	Operating temperature	240V	HP	3
		240V min	HP °C	-25



ROTARY CAM SWITCH GX SERIES, CHANGEOVER SWITCH 1 POLE 32A, FOR FRONT MOUNTING WITH BLACK HANDLE, FRONT PLATE 65X65MM

	max	°C	+70
Resistance & Protection			
Frontal IP degree			IP65
Terminals IP degree			IP20
Dimensions			






Drillings for 4 screws fixing (4V version).

Series	Dimensions						L Number of elements												
	□A	C	ØD1	ØD2	Е	□K	□N	1	2	3	4	5	6	7	8	9	10	11	12
GX16	48	39.5	12	5	26.5	36	6	43	51.5	60	68.5	77	85.5	94	102.5	111	119.5	128	136.5
GX20	48	39.5	12	5	26.5	36	6	43	51.5	60	68.5	77	85.5	94	102.5	111	119.5	128	136.5
GX32	65	53	14	5	34.5	48	7	51	63	75	85	99	111	123	135	147	159	171	183
GX40	65	53	14	5	34.5	48	7	51	63	75	85	99	111	123	135	147	159	171	183

## Wiring diagrams



## Certifications and compliance

Compliance

CSA C22.2 n° 14

IEC/EN/BS 60947-1

IEC/EN/BS 60947-3

IEC/EN/BS 60947-5-1

IEC/EN/BS 61058-1

UL60947-4-1

Certificates

cULus

EAC

ETIM classification

ETIM 8.0

GX3251U

EC001105 - Offload switch