

# ROTARY CAM SWITCH GX SERIES, CHANGEOVER SWITCH 3 POLES 32A, FOR FRONT MOUNTING WITH BLACK HANDLE, FRONT PLATE 65X65MM



				Determine
Product designation				Rotary cam switches
Product type designation	on			GX32
General characteristics				
Switching diagram				53 - Changeover switch 3 poles - 2 speed motor starting with separate windings
N° of elements				3
Mounting form				U - Front mounting with black handle
Contact characteristics				
Rated insulation voltage	e Ui	IEC/EN UL/CSA	V V	690 600
Rated impulse withstan	d voltage Uimp		kV	6
Conventional free air th	ermal current Ith			
		IEC/EN UL/CSA	A A	32 32
Rated operational volta			V	440
Rated operational impu			kV	4
Maximum fuse size for	short-circuit protection In (gG)			
		10kA	Α	35
		15kA	A	35
Data dahari tiran ayraa	41	25kA	A	35
Rated short time currer	IT ICW	4.0	L.Λ	1000
Conductivity		1s	kA	1000 10/5 mA/V
Conductivity Operational current le I	EC/EN			10/5 IIIA/ V
Operational current le i	AC1/AC21A			
	7.0 17.02 17.		Α	32
	AC15			
		110V	Α	25
		220/230V	Α	20
		380/400V	Α	10
		660/690V	Α	2
Rated operational power				
	Three-phase AC-3			
		220/230V	kW	7.5
		380/440V	kW	11
	Single phase AC 2	500/690V	kW	
	Single-phase AC-3	110V	kW	1.8




# ROTARY CAM SWITCH GX SERIES, CHANGEOVER SWITCH 3 POLES 32A, FOR FRONT MOUNTING WITH BLACK HANDLE, FRONT PLATE 65X65MM


		220/230V	kW	3.5
		380/440V	kW	5.5
	Three-phase AC23A			
		220/230V	kW	8
		380/440V	kW	15
		500/690V	kW	15
	Single-phase AC23A	300/030 V	IVV	10
	Single-phase ACZSA	110\/	LANA	2.2
		110V	kW	2.2
		220/230V	kW	3.5
		380/440V	kW	6
Rated operational curre				
	DC21A			
		48V	Α	32
		60V	Α	32
		110V	Α	5
		220V	Α	0.8
		440V	Α	0.25
	DC23A (poles in series)			
	(F <b>5555</b> )	24V	Α	32 (1)
		48V	A	32 (2)
		60V	A	32 (3)
		110V	A	15 (3)
	==::	220V	Α	12 (4)
	DC13			
		24V	Α	32
		48V	Α	25
		60V	Α	14
		110V	Α	3
		220V	Α	0.5
		440V	Α	0.15
Power dissipation		<u> </u>	W	1.6
Mechanical features				
Terminals screw				M4
	orminala may		Nm	1.2
Tightening torque for to	errillidis max		INIII	1.2
Conductor size	NWO 51 11 11			
	AWG - Rigid cable			
		min	AWG	16
		Max	AWG	8
	AWG - Flexible cable			
		min	AWG	16
		Max	AWG	10
	Conductor size (IEC) - Flexible cable			_
	` '	min	mm²	1.5
		Max	mm²	6
	Conductor size (IEC) - Rigid cable	man		=
	Solidation Size (IEO) - Migid cable	min	mm²	1.5
Manhania de l'étre		Max	mm²	10
Mechanical life			cycles	1X10 <sup>6</sup>
UL technical data				
Motor power for direct-				
	for three-phase motor			
		120V	HP	3
		240V	HP	7.5
		480V	HP	15



### ROTARY CAM SWITCH GX SERIES, CHANGEOVER SWITCH 3 POLES 32A, FOR FRONT MOUNTING WITH BLACK HANDLE, FRONT PLATE 65X65MM

		600V	HP	15
	for single-phase motor			
		120V	HP	1.5
		240V	HP	3
Ambient conditions				
Temperature				
	Operating temperature			
		min	°C	-25
		max	°C	+55
	Storage temperature			
		min	°C	-40
		max	°C	+70
Resistance & Protecti	on			
Frontal IP degree				IP65
Terminals IP degree			•	IP20
Dimensions				






Drillings for 4 screws fixing (4V version).

Corios				L Number of elements															
Series	□A	C	ØD1	ØD2	E	□K	□N	1	2	3	4	5	6	7	8	9	10	11	12
GX16	48	39.5	12	5	26.5	36	6	43	51.5	60	68.5	77	85.5	94	102.5	111	119.5	128	136.5
GX20	48	39.5	12	5	26.5	36	6	43	51.5	60	68.5	77	85.5	94	102.5	111	119.5	128	136.5
GX32	65	53	14	5	34.5	48	7	51	63	75	85	99	111	123	135	147	159	171	183
GX40	65	53	14	5	34.5	48	7	51	63	75	85	99	111	123	135	147	159	171	183

#### Wiring diagrams



### Certifications and compliance

### Compliance

CSA C22.2 n° 14

IEC/EN/BS 60947-1

IEC/EN/BS 60947-3

IEC/EN/BS 60947-5-1

IEC/EN/BS 61058-1

UL60947-4-1



**ENERGY AND AUTOMATION** 

#### GX3253U

ROTARY CAM SWITCH GX SERIES, CHANGEOVER SWITCH 3 POLES 32A, FOR FRONT MOUNTING WITH BLACK HANDLE, FRONT PLATE 65X65MM

Certificates				
	cULus			
	EAC			
ETIM elegationtic	10.			

ETIM classification

ETIM 8.0 EC001105 - Off-load switch