

ROTARY CAM SWITCH GX SERIES, VOLTMETER SWITCH FOR PHASE-PHASE VOLTAGES 40A, FOR FRONT MOUNTING WITH BLACK HANDLE, FRONT PLATE 65X65MM

Product designation		Rotary cam
•		switches
Product type designation General characteristics		GX40
Switching diagram		67 - Voltmeter switch for phase- phase voltages
N° of elements		2
Mounting form		U - Front mounting with black handle
Contact characteristics		
Rated insulation voltage Ui		
IEC/EN	V	690
UL/CSA	V	600
Rated impulse withstand voltage Uimp	kV	6
Conventional free air thermal current Ith		
IEC/EN	Α	40
UL/CSA	Α	40
Rated operational voltage	V	440
Rated operational impulse voltage	kV	4
Maximum fuse size for short-circuit protection In (gG)		
10kA	Α	40
15kA	Α	35
25kA	Α	35
Rated short time current lcw		
1s	kA	1000
Conductivity		10/5 mA/V
Operational current le IEC/EN		
AC1/AC21A	۸	40
1045	A	40
AC15	۸	25
110V 220/230V	A	25 22
380/400V	A A	12
660/690V	A	2
Rated operational power in AC		
Three-phase AC-3		
220/230V	kW	7.5
380/440V	kW	15
500/690V	kW	15
Single-phase AC-3		<u> </u>
110V	kW	2.2
220/230V	kW	4.4
380/440V	kW	7
Three-phase AC23A		
220/230V	kW	9
380/440V	kW	18.5
500/690V	kW	15
Single-phase AC23A		
110V	kW	3
220/230V	kW	5.2
380/440V	kW	7.5
Rated operational current in DC		




ROTARY CAM SWITCH GX SERIES, VOLTMETER SWITCH FOR PHASE-PHASE VOLTAGES 40A, FOR FRONT MOUNTING WITH BLACK HANDLE, FRONT PLATE 65X65MM


	DC21A	4017	_	4.0
		48V	A	40
		60V	A	40
		110V	A	6
		220V	A	0.8
	B0004 (1 : : :)	440V	Α	0.25
	DC23A (poles in series)	6 A) (10 (1)
		24V	A	40 (1)
		48V	A	40 (1)
		60V	A	40 (3)
		110V	A	40 (3)
	D040	220V	Α	12 (4)
	DC13	0.417	Δ.	40
		24V	A	40
		48V	A	32
		60V	A	16
		110V	A	3
		220V	A	0.5
		440V	A	0.15
Power dissipation			W	1.6
Mechanical features				244
Terminals screw				M4
Tightening torque for te	erminals max		Nm	1.2
Conductor size				
	AWG - Rigid cable	_		
		min	AWG	16
		Max	AWG	8
	AWG - Flexible cable	_		
		min	AWG	16
	-	Max	AWG	10
	Conductor size (IEC) - Flexible cable	_		
		min	mm²	1.5
		Max	mm²	6
	Conductor size (IEC) - Rigid cable	_		
		min	mm²	1.5
		Max	mm²	10
Mechanical life			cycles	1X10 ⁶
UL technical data				
Motor power for direct-				
	for three-phase motor	4001		F
		120V	HP	5
		240V	HP	10
		480V	HP	15
		600V	HP	15
	for all and a second to a			
	for single-phase motor	400)/		
	for single-phase motor	120V	HP	2
A mala i a materia manaditi	for single-phase motor	120V 240V		2 5
Ambient conditions	for single-phase motor		HP	
Ambient conditions Temperature			HP	
	for single-phase motor Operating temperature	240V	HP HP	5
		240V min	HP HP	-25
	Operating temperature	240V	HP HP	5
		240V min max	HP HP °C °C	-25 +55
	Operating temperature	240V min	HP HP	-25

ENERGY AND AUTOMATION

ROTARY CAM SWITCH GX SERIES, VOLTMETER SWITCH FOR PHASE-PHASE VOLTAGES 40A, FOR FRONT MOUNTING WITH BLACK HANDLE, FRONT PLATE 65X65MM

	max	$^{\circ}\mathrm{C}$	+70
Resistance & Protection			
Frontal IP degree			IP65
Terminals IP degree			IP20
Dimensions			






Drillings for 4 screws fixing (4V version).

Series	Dimensions							L Number of elements											
	□A	C	ØD1	ØD2	Е	□K	□N	1	2	3	4	5	6	7	8	9	10	11	12
GX16	48	39.5	12	5	26.5	36	6	43	51.5	60	68.5	77	85.5	94	102.5	111	119.5	128	136.5
GX20	48	39.5	12	5	26.5	36	6	43	51.5	60	68.5	77	85.5	94	102.5	111	119.5	128	136.5
GX32	65	53	14	5	34.5	48	7	51	63	75	85	99	111	123	135	147	159	171	183
GX40	65	53	14	5	34.5	48	7	51	63	75	85	99	111	123	135	147	159	171	183

Wiring diagrams



Certifications and compliance

Compliance

CSA C22.2 n° 14

IEC/EN/BS 60947-1

IEC/EN/BS 60947-3

IEC/EN/BS 60947-5-1

IEC/EN/BS 61058-1

UL60947-4-1

Certificates

cULus

EAC

ETIM classification

ETIM 8.0

EC001029 -Selector switch, complete